PRODUCT INFORMATION PACKET



Model No: 193344.60 Catalog No: 193344.60

LEESON® PASSPORT 7.50 HP General Purpose, 3 phase, 1200 RPM, 230/460 V, 132M Frame, TEFC










Nameplate Specifications

Phase	3	Output HP	7.50 & 5 Hp
Output KW	5.6 & 3.7 kW	Voltage	230/460 & 200/400 V
Speed	1185 & 990 rpm	Service Factor	1.15 & 1.15
Frame	132M	Enclosure	Totally Enclosed Fan Cooled
Thermal Protection	No Protection	Efficiency	91 & 90.2 %
Ambient Temperature	40 °C	Frequency	60 & 50 Hz
Current	21.6/10.8 & 19/9.5 A	Power Factor	72
Duty	Continuous	Insulation Class	F
Design Code	В	KVA Code	Н
Drive End Bearing Size	6308	Opp Drive End Bearing Size	6306
UL	Recognized	CSA	Υ
CE	Υ	IP Code	55
Number of Speeds	1		


Technical Specifications

Electrical Type	Squirrel Cage Inverter Rated	Starting Method	Wye Start Delta Run Or Inverter					
Poles	6	Rotation	Reversible					
Resistance Main	0 Ohms	Mounting	Rigid Base					
Motor Orientation	Horizontal	Drive End Bearing	Ball					
Opp Drive End Bearing	Ball	Frame Material	Cast Iron					
Shaft Type	IEC	Overall Length	18.26 in					
Shaft Diameter	1.500 in	Shaft Extension	3.15 in					
Assembly/Box Mounting	F3							
Outline Drawing	SS622263	Connection Drawing	004172.01					


This is an uncontrolled document once printed or downloaded and is subject to change without notice. Date Created:06/21/2023



WYE - DELTA STARTING USEABLE ON 2,4 AND 6 POLE MOTORS.



REFER TO THE WYE-DELTA STARTER CONNECTION INSTRUCTIONS FOR PROPER CONNECTION OF POWER LINES TO STARTER.



REFER TO THE CUTLER — HAMMER OR EQUIV. FOR PROPER SELECTION OF OVERLOAD HEATER COILS.

				UNLES	ERANCES S SPECIFIED				ELECTRIC	MOTOR	S	DRAWN	WLW 09/0	18/77
				DEC.	INCHES		3=5	(•)	GEARM	OTORS		снк	RPB 09/12,	/77
				.x	±.1				J AND D	PRIVES		APPD	JCW 09/12	<u>!</u> /77
03	REV'D LOW VOLTAGE CONN. LEADS PER ELEC.	BJB 06/07/00		.xx	±.01	TITLE	DELTA -	WYE	CONNECTION	DIAGRA	·Μ	SCALE	1=1	
02	ADDED T-STAT. NOTES PER ELECTRICAL	KMM 06/02/98		.xxx	±.005							REF		
01	REDRAWN TO CAD	DBT 06/02/97		.xxxx	±.0005	MAT'L.						FMF		
NO.	REVISION	BY & DATE	снк	ANG	±1/2°	FINISH						PREV		
THIS DRAWING IN DESIGN AND DETAIL IS OUR PROPERTY AND MUST NOT BE USED EXCEPT RFP						CAD FILE	0	041720	1	SIZE DRA				REV.
IN CONNECTION WITH OUR WORK ALL RIGHTS OF DESIGN AND INVENTION ARE RESERVED THIS IS AN ELECTRONICALLY GENERATED DOCUMENT — DO NOT SCALE THIS PRINT										A	004	172-	-01	03

ROTATION CAN BE REVERSED BY INTERCHANGING ANY TWO LINE LEADS

• RED LEADS OR P1, P2, FOR N/C THERMOSTAT

ACROSS THE LINE START & RUN							
	LINE 1	LINE 2	LINE 3	JOIN & INSULATE SEPARATELY			
HIGH VOLT	T1,T12	T2,T10	T3,T11	(T4,T7) (T5,T8) (T6,T9)			
LOW VOLT	T1,T6 T7,T12	T2,T4 T8,T10	T3,T5 T9,T11				

