Product Information Packet: Model No: 326TSTDCD4022, Catalog No:U517A Fire Pump Motor, 60 HP, 3 Ph, 60 Hz, 190/380-400 V, 3600 RPM, 326TS Frame, DP



## Nameplate Specifications

Phase	3	Output HP	60 Hp	
Output KW	45.0 kW	Voltage	190/380-400 V	
Speed	3565 rpm	Service Factor	1.15	
Frame	326TS	Enclosure	Drip Proof	
Thermal Protection	No Protection	Efficiency	93 %	
Ambient Temperature	50 °C	Frequency	60 Hz	
Current	165.0/82.5-77.5 A	Power Factor	88	
Duty	Continuous	Insulation Class	F	
Design Code	В	KVA Code	F	
Drive End Bearing Size	6212	Opp Drive End Bearing Size	6212	
UL	Listed	CSA	Υ	
CE	Υ	IP Code	23	
Number of Speeds	1			

## **Technical Specifications**

Electrical Type	Squirrel Cage Induction Run	Starting Method	Part Wdg Start & Wye Start Delta Run
Poles	2	Rotation	Reversible
Resistance Main	.138 Ohms	Mounting	Rigid Base
Motor Orientation	Horizontal	Drive End Bearing	Ball
Opp Drive End Bearing	Ball	Frame Material	Cast Iron
Shaft Type	тѕ	Overall Length	28.23 in
Frame Length	15.74 in	Shaft Diameter	1.875 in
Shaft Extension	3.75 in	Assembly/Box Mounting	F1/F2 CAPABLE
Outline Drawing	0232400025-326TS	Connection Drawing	EE7308AA

This is an uncontrolled document once printed or downloaded and is subject to change without notice. Date Created:09/07/2024