Product Information Packet: Model No: LM80237, Catalog No:LM80237 Fire Pump Motor, 250 HP, 3 Ph, 60 Hz, 400 V, 1800 RPM, 447TS Frame, DP

Nameplate Specifications

Output HP	250 Hp	Output KW	187.0 kW
Frequency	60 Hz	Voltage	400 V
Current	320.0 A	Speed	1788 rpm
Service Factor	1.15	Phase	3
Efficiency	95.5 %	Power Factor	87
Duty	Continuous	Insulation Class	F
Design Code	В	KVA Code	F
Frame	447TS	Enclosure	Drip Proof
Thermal Protection	No Protection	Ambient Temperature	50 °C
Drive End Bearing Size	6319	Opp Drive End Bearing Size	6317
UL	No	CSA	Y
CE	Y	IP Code	23
Number of Speeds	1		

Technical Specifications

Electrical Type	Squirrel Cage Induction Run	Starting Method	Part Wdg Start & Wye Start Delta Run
Poles	4	Rotation	Reversible
Resistance Main	.022 Ohms	Mounting	Rigid Base
Motor Orientation	Horizontal	Drive End Bearing	Ball
Opp Drive End Bearing	Ball	Frame Material	Cast Iron
Shaft Type	тѕ	Overall Length	45.95 in
Frame Length	31.10 in	Shaft Diameter	2.375 in
Shaft Extension	4.75 in	Assembly/Box Mounting	F1/F2 CAPABLE
Connection Drawing	EE7300BH	Outline Drawing	SS620256

This is an uncontrolled document once printed or downloaded and is subject to change without notice. Date Created:09/16/2022